

The following instructions will walk you through how to change the APN code for the Videofied XL600 control panel.

1. With the display showing the disarmed level with the date and time stamp press the RIGHT ARROW until you see ACCESS LEVEL # displayed

DATE / TIME
DISARMED LVL: 3

2. Press YES on ACCESS LEVEL and use the ARROW KEYS to change the ACCESS LEVEL to LVL: 4

ACCESS LEVEL 4

3. With the display showing BADGE or CODE enter 4321 followed by YES

4. RIGHT arrow until the display shows CONFIGURATION and press YES

CONFIGURATION

5. With the display showing BADGE or CODE enter 4321 followed by YES

6. Display will show GENERAL PARAMETERS, press YES

GENERAL PARAMETERS

7. Display will show SITE IDENTIFICATION press the LEFT ARROW until it shows GPRS PARAMETERS and press YES

GPRS PARAMETERS

8. With the display showing APN CODE press YES then enter your APN code followed by YES.

CAMERA
CAMERA 1

Notes:

The CLR button will delete the previous character entered.

The 1, 0, and @ symbol allow for additional characters.

Button	1st press	2nd press	3rd press	4th press	5th press	6th press	7th press	8th press	9th press	10th press	11th press
1	space	.	,	?	!	;	:	1			
2	A	B	C	2							
3	D	E	F	3							
4	G	H	I	4							
5	J	K	L	5							
6	M	N	O	6							
7	P	Q	R	S	7						
8	T	U	V	8							
9	W	X	Y	Z	9						
0	-	+	=	/	¥	-	<	>	()	0	