



Product Summary

The Exterior Siren/Strobe Model SE650/SE550/SE750 is a wireless siren designed for use in RSI VIDEO TECHNOLOGIES™ security systems. The siren includes the following features:

- > Totally wireless, battery operated
- > Weather-resistant enclosure
- > Dual tamper function provides detection for both wall and cover tamper.
- > Transmits check-in/status signal every 8 minutes

Installation Guidelines



For easier installation, programming and RF testing should be done to check for good communication between the control panel and all system devices before mounting system devices. Install the siren and other system devices in the following order:

- > Programming/RF Testing—program siren and all other devices into the control panel and test RF communication from each intended device location to the control panel.
- > Mounting—mount siren at the tested location.

Programming/RF Testing

The following provides summarized steps for device programming and testing. For complete details, refer to the control panel installation manual.

- 1 Remove four cover screws, separate cover from siren and install batteries.
- 2 Put control panel into programming/configuration mode.
- 3 Using a programmed alphanumeric keypad, proceed through menus until the display shows ADD A NEW DEVICE.
- 4 Press Yes. The display shows PRESS PROGRAM BUTTON OF DEVICE.
- 5 Press and release program button on siren using a paper clip end. The siren LED flashes. Wait for keypad display to show SIREN (1 - 24) RECORDED.




- 6 Press Yes. The display shows RADIO RANGE TEST? Press Yes again. The siren LED starts flashing and keypad display shows TEST IN PROGRESS.
- 7 Take siren to its intended mounting location and make sure LED flashes continuously, indicating good communication with control panel.
- 8 Press Yes to end radio range test, then press Esc/No.
- 9 The display shows ADD A NEW DEVICES? Repeat steps 4 - 8 for remaining sirens.
- 10 When finished, exit from configuration mode.

Mounting

- > Use proper tools and hardware for mounting the unit.
- > Mount outdoors under eaves to help prevent direct contact from elements.
- > Mount on front of structure where strobe light is clearly visible to responding authorities.

- 1 Remove batteries.
- 2 Hold unit up against mounting surface and mark the three mounting holes.
- 3 Drill pilot holes and install anchors where needed.
- 4 Place unit on mounting surface so mounting holes line up with pilot holes/anchors and secure unit with appropriate screws.
- 5 Install batteries, observing correct polarity.
- 6 Place the flash wire of the cover to the siren.
- 7 Attach front cover.



Mounting Holes

Regulatory Information

FCC Part 15

This device complies with FCC Rules Part 15.

Operation is subject to the following two conditions:

- 1.) This device may not cause harmful interference and,
- 2.) this device must accept any interference that may be received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by RSI VIDEO TECHNOLOGIES, Inc. can void the user's authority to operate the equipment.

Specifications

| | |
|---------------------------|---|
| Panel Compatibility | VIDEOFIED V6000/VISIO1000/V7000 |
| Operating Frequency | 915/868/920 MHz |
| Radio type | Spread Spectrum Bidirectional RF |
| Power Requirements | Four 1.5 V Alkaline batteries |
| Battery Type | D size alkaline |
| Power Output | 105 dB @ 1 meter |
| Operating Temperature | -13° - 158° F (-25° - +70° C) |
| Maximum Relative Humidity | 70%, non-condensing |
| Dimensions | (LxWxD): 9 in. x 6-1/2 in. x 3 in. (227 mm x 166 mm x 80 mm) |
| Weight | 31 oz./880 g (without batteries) |
| Approvals | UL / FCC (SE650) CE / EN50131 / EN300220 / INCERT/ IDA / NCP (SE550) A-Tick (SE750) |



EMEA SALES
 2, rue Alexis de Tocqueville
 92160 ANTONY
 FRANCE
 Phone +33 (0)1 55 59 10 25
 Fax +33 (0)3 90 20 66 36

USA SALES
 4455 White Bear Parkway, Suite 700
 White Bear Lake, MN 55110
 USA
 Phone 877-06-5800
 Fax 651-762-4693

www.videofied.com

© 2007 RSI VIDEO TECHNOLOGIES™ Videofied® is a Registered Trademark of RSI VIDEO TECHNOLOGIES™.
 S'View® is a registered trademark of RSI VIDEO TECHNOLOGIES™. Specifications subject to change without notice.